







Mizar30 recessed series installation instructions

MODEL	Dimensions	Splicing size	Cut-Out
LR00203 LR00204 LR00207	94*38*56mm	89*38*56mm	89*32mm
	178*38*56mm	172*38*56mm	172*32mm
	344*38*56mm	338*38*56mm	338*32mm
	510*38*56mm	505*38*56mm	505*32mm
	1010*38*56mm	1005*38*56mm	1005*32mm




Precautions:




- 1、 Please perform wiring and installation work when the power is off!
- 2、 Make holes in the ceiling according to the cutout of the corresponding model
- 3、 The wiring terminals are not load-bearing, and the wires shall not be lifted during installation!
- 4、 The maximum total length of splicing cannot exceed 5 meters ,
- Total power in series connection shall not exceed 120W
- 5、 T-shaped splicing and cross-shaped splicing can be spliced according to L-shaped splicing.
- 6、 The specific appearance is subject to the actual product!

I Installation Instructions for single lamp((constant voltage):







II Installation for Connection:






III Installation Instructions for single lamp(Constant Current):



- This product is only suitable for indoor, it is not allowed to be rinsed with water.
- Independent external driver, recessed mounted.



- Use only drivers that comply with IEC or CE safety standards.
- Check if the power supply match with the luminaire.
- Must consider the maximum current value displayed on the label of the luminaire.
- The voltage displayed on the luminaire is not used to select the constant voltage driver, but the voltage covered by the selected constant current driver.
- Take suitable ESD measures to avoid touching bare conductors.
- LED chips can be damaged if be in touch with chemical material or gas. Therefore, it is not allowed to clean the LED housing or luminaire by chemicals.
- The following items are confirmed to have negative impact on the performance of the luminaire, avoid to keep luminaire in the same circumstance with them.
 - Methyl acetate or ethyl acetate (i.e., nail polish remover)
 - Cyanoacrylates (i.e., "Superglue")
 - Glycol ethers (including Radio Shack @ Precision Electronics Cleaner - dipropylene glycol monomethyl ether)
 - Formaldehyde or butadiene (including Ashland PLIOBOND @ adhesive)
 - Dymax 984-LVUF conformal coating
 - Loctite Sumo Glue, Loctite 384 adhesive, Loctite 7387 activator
 - Gorilla Glue, Bleach, Bleach-containing cleaners, sprays
- Remove the insulation material from the luminaire or provide enough space so that the temperature raising will not overpass the limited TC.
- LED chip is very sensitive to switching transients, therefore, LED lamps and appliances must be connected after power cut off, no hotswappable.
- Recommends using the driver indicated on the luminaire manual.
- Must consider the polarity of the product.
- It is recommended to use an ambient temperature of -10 ° C to 40 ° C for indoor lighting equipment
- If the external flexible cable or cord of this lamp is damaged, the cord should be replaced by the manufacturer or its service agent or a similarly qualified person
- The light source in this lamp should be replaced by the manufacturer or its service agent or a similarly qualified person